

EECS 373
Exam 1
Winter 2005
February 24, 2005

Name:

University of Michigan unickname:

Open book, open notes. Calculators are permitted, but no laptops, PDAs, cell phones, etc. This exam has four problems in this packet, plus one bus interface design problem in a separate packet. Please be sure to put your name and unickname on BOTH packets. Problems vary in difficulty; it is strongly recommended that you do not spend too much time on any one problem.

The rules of the Honor Code of the University of Michigan College of Engineering apply for this exam.

Honor code pledge: I have neither given nor received aid on this examination, nor have I concealed any violations of the Honor Code.

Signature:

(examinations without a signed honor pledge will not be graded)

1. Memory types (12 points):

You are given the task of designing a portable scientific instrument that will be used to acquire sensor data and process it. Sensor data is acquired at very high speed into a fast memory; this is controlled with specialized logic implemented in an FPGA. After acquisition, the processing is done with a conventional microprocessor using a program that is stored on the instrument. This processing requires a fairly large memory, but extreme speed is not required. The system is exposed to severe mechanical shock and vibration, so you cannot use a hard drive. All storage must be implemented with electronic memory components. The system has the following storage requirements:

- 64 megabyte filesystem to store the program and data processing results
- 512 megabyte main memory for the microprocessor (moderate speed)
- 4 megabyte buffer for sensor data acquisition (very high speed)
- 2 megabyte storage for the bit file used to program the FPGA

The system will have the program and FPGA bit file installed in the lab. It will be taken into the field, used to collect results, and then returned to the lab. Back at the lab, processed results will be retrieved and updated processing programs and FPGA bit files will be installed before the instrument is returned to the field. Note that the memory internal to the FPGA chip is volatile; it must be programmed from the bit file at each system power up.

From the following choices select the one MOST APPROPRIATE type of memory for each system function:

- mask programmable read only memory (ROM)
- fuse programmable read only memory (PROM)
- diode programmable write only memory (DWOM)
- dynamic random access memory (DRAM)
- static random access memory (SRAM)
- flash memory (FLASH)

----- 64 megabyte filesystem

----- 512 megabyte main memory

----- 4 megabyte high speed sensor data buffer

----- 2 megabyte FPGA bit file storage

2. Asynchronous serial communication (5 points):

Consider an asynchronous serial data connection with 1 start bit, 8 data bits, and 1 stop bit. This is a very basic asynchronous connection; there is no bit stuffing, no adaptive clocks, no parity bit, absolutely nothing fancy. The receiver has been designed so that it attempts to sample the received data near the center of the appropriate time for each bit.

Approximately how much total clock frequency mismatch between the transmitter and the receiver can be tolerated without causing errors?

(Example: if the transmitter ran at 101 KHz and the receiver ran at 99 KHz, this would be about a 2% mismatch.)

Select the one best answer from the choices below:

- (a) 0%; the transmitter and receiver clocks must match exactly or there will eventually be errors if a long enough message is sent.
- (b) about a 5% mismatch is tolerable
- (c) about a 12% mismatch is tolerable
- (d) about a 50% mismatch is tolerable
- (e) there is no limit to the clock frequency mismatch; with asynchronous serial communication, accurate data transmission does not depend at all on having matched clock frequencies.

3. USB communications (*18 points*):

The basic clock rate of a high speed USB bus is 480 MHz. Each bit transmitted takes one clock period. Thus, the raw data rate on the wires is 480 megabits per second. A certain, unknown data pattern is being transmitted. Standard USB signalling (bit stuffing and encoding) is being used. You connect an oscilloscope to the USB bus and discover that the transmitted data is a symmetric 240 MHz square wave.

What bit pattern is being sent, before bit stuffing and encoding has been applied? (In other words, what bit pattern, after bit stuffing and encoding, will turn into a symmetric 240 MHz square wave?)

What is the lowest frequency symmetric square wave you might observe on the wires? (calculator optional; a correct answer given as a fraction or other expression will be accepted for full credit).

What bit pattern would have to be sent to produce this?

4. PowerPC assembly language and EABI (30 points):

Below is a small function and an attempt to implement it as a PowerPC EABI compliant assembly language program. All variables are unsigned integers. The assembly language program contains numerous errors; find them. Don't worry about wasteful or inefficient code. Only report errors that will cause this to fail to assemble, fail to implement the specified function correctly, or violate the EABI interface. For each line on which you find an error, give the line number and a very brief description of the error. It is possible for a line to have more than one error. For errors without specific line numbers (such as if something important is left out), write "missing" instead of the line number. Three errors are given as examples.

```
fun(w,x,y,z) {
    w = ggg(w)
    a = w + 67890;
    b = (x + y) & -4
    c = hhh(987654321, 555555, z, 7)
    d = z + c
    e = (b - a) + 5
    return(e)
}

fun: stwu    r1,-30(r1)      #line 1
     stw     r29,8(r1)      #line 2
     stw     r30,12(r1)     #line 3
     mfspr   r0,LR          #line 4
     stw     r0,4(r1)       #line 5
     addi    r29,r3,67890   #line 6
     lis     r3,big@h       #line 7
     ori     r3,r3,big@l    #line 8
     add     r14,r4,r5       #line 9
     andi.   r30,r14,-4     #line 10
     ori     r4,r0,7        #line 11
     ori     r5,r5,555555@l #line 12
     lis     r5,555555@h    #line 13
     bl     hhh             #line 14
     add     r11,r6,r3      #line 15
     sub     r0,r29,r30     #line 16
     addi    r12,r0,5       #line 17
     add     r5,r11,r12     #line 18
     lwz    r30,8(r1)       #line 19
     lwz    r29,12(r1)     #line 20
     blr                               #line 21
     crash  r56             #line 22

big .word 987654321
```

(continued from previous page)

List of errors found:

22: nonexistent instruction "crash"

22: invalid register number "r56"

missing: function "w = ggg(w)" is never called

(find as many more errors as you can, full credit for 15 additional errors)
